Data Sheet Single Phase EMI Filter – MF150 IEC Inlet with fuse (Medical Version)



Description

These series range of IEC Inlet type filters with fuse are designed to suppress undesirable electrical disturbances in Power Lines. They limit the amplitude of interfering voltages on AC power lines and prevent them from propagating into or out of the filtered equipment.

Features

Integral IEC Connector Excellent performance/size ratio Single/Double Fuse Option Rated current up to 10A Ultra-low leakage current High conducted attenuation performance

Applications


Medical Equipment Diagnostic Equipment X-Ray Machines Low Leakage Applications

Typical circuit Diagram



Safety Approval & Compliance





Technical Specifications

Maximum Continuous Operating Voltage	: 250VAC		
Operating Frequency	: 50/60Hz		
Current ratings	: 1A to 10A @40°C		
High Potential test voltage	: L to G 2250VDC for 1 Minute		
	L to L 1450VDC for 1 Minute		
Overload Capability	: 135% of Rated current for 15 minutes		
Design Corresponding to	: UL1283, CSA 22.2 No.8-13 and IEC 60939		
Flammability corresponding to	: UL 94 V-0		
Temperature range	: -25°C to +85ºC		
Climatic Category	: 25/85/21		
Enclosure Material	: Aluminium		

Images shown above are just for reference


Selection Table

Part Number	Ordering Code	Rated Current @40°C	Leakage Current @250VAC (μA)	Termination	Weight (Grams)
MF150 - 01	S150SF0001D	1A	5	Fastons 6.3 X 0.8mm	60
MF150 - 03	S150SF0003D	3A	5	Fastons 6.3 X 0.8mm	60
MF150 - 06	S150SF0006D	6A	5	Fastons 6.3 X 0.8mm	60
MF150 - 10	S150SF0010D	10A	5	Fastons 6.3 X 0.8mm	60

Note:

Ordering code mentioned above is for single fuse, for Dual fuse replace SF to DF in the Ordering Code *[Ex: For 1A with Dual Fuse: S310DF0001D]*


Mechanical Drawing



All dimensions in mm; Tolerances according to ISO2768-m

47.5±0.5

Insertion Loss – (Common Mode)



EMI Solutions Private Ltd.

#237-A5, Bommasandra Industrial Area, Bangalore-560099, Marketing: +91 80 27836880, Email: marketing@emisindia.com